

Switching Spark Gap

CAS02X-093

Ordering code: B88069X0930T502

DC spark-over voltage ^{1) 2)}	180	180 220			
Initial values					
Ignition time t_I after 150 hours in darkness $^{3)}$	95	99.9	100	%	
at –20 °C at +25; 125 °C	≤ 4 ≤ 2	≤ 5 ≤ 3	≤ 7 ≤ 4	S S	
Electrical life time					
Maximum increase of DC spark-over voltage	25	25			
Switching operations at +25; 125 °C Switching frequency 10 … 25 Hz Switching frequency < 10Hz		2 000 000 4 000 000			
Test circuit parameters Open circuit voltage V _{0'} Loading resistance R Discharge capacitance C Inductance L Discharge peak current I _P	230 15 2.2 10 ~ 300			V _{ac} kΩ μF μH A	
Insulation resistance at 100 V _{dc}	> 0.1	> 0.1			
Capacitance at 1 MHz	< 2	< 2			
Weight	~ 1.5	~ 1.5			
Operation and storage temperature	-20 ·	-20 +125			
Climatic category (IEC 60068-1)	20/ 12	20/ 125/ 21			
Marking, red	EPCC CS 230 YY MM O	230 - Nominal voltageYY - Year of productionMM - Month of production			

At delivery AQL 0.65 level II, DIN ISO 2859
In ionized mode, after load
Time from capacitor charged to the first high voltage spark Test circuit: V_{ac} = 198 V; R = 36 kΩ; C = 2.2 μF



Switching Spark Gap

CAS02X-093

Ordering code: B88069X0930T502



© EPCOS AG 2002. Reproduction, publication and dissemination of this data sheet, enclosures hereto and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.